

Symbol	Name	Type				Quantity	Note
		Phase 3, 50Hz, 380V	Phase 1, 50Hz, 220V	Phase 3, 60Hz, 220V	Phase 1, 60Hz, 110V/220V		
M	Induction Motor	Y90S-4 1.1 KW 1420r/min	YL90S-4 1.1KW 1420r/min	Y90S-4 1.1KW 1720r/min	YC90L-4 1.1KW 1720r/min	1	
KM1	AC Contactor	3TB41 Control volta 24V	3TB41 Control volta 24V	3TB43 Control volta 29V	3TB43 Control volta 29V	1	Siemens Contactor
KM2	"	"	"	"	"	1	Siemens Contactor
KM3	"	"	"	"	"	1	Siemens Contactor
FR	Heating device relay	JR16B-20/3 3.5A	JR16B-20/3 11A	JR16B-20/3 5A	YJR16B-20/3 22A	1	
TC	Transformer for Control circuit Supply	BKC-50 Primary: 0-380V Secondary: 0-6V, 0-24V	BKC-50 Primary: 0-220V Secondary: 0-6V, 0-24V	BKC-50 Primary: 0-220V Secondary: 0-6V, 0-29V	BKC-50 Primary: 0-110V-220V Secondary: 0-6V, 0-29V	1	
FU1	Fuse	BLF-1 2A	BLF-1 2A	BLF-1 2A	BLF-1 2A	1	
FU2	"	BLF-1 1A	BLF-1 1A	BLF-1 1A	BLF-1 1A	1	
SA (CS)	Selector Switch	HZ5B-10/2 D009	HZ5B-10/2 D009	HZ5B-10/2 D009	HZ5B-10/2 D009	1	
SB1	Reset	LAY3-01 ZS/1	LAY3-01 ZS/1	LAY3-01 ZS/1	LAY3-01 ZS/1	1	
SB2	Power start	LA19-11D Green	LA19-11D Green	LA19-11D Green	LA19-11D Green	1	Voltage for Lamp 6.3 V
SB3	Inching	LA19-11 Black	LA19-11 Black	LA19-11 Black	LA19-11 Black	1	
HL	Indicator lamp	XD-1 White	XD-1 White	XD-1 White	XD-1 White	1	Voltage for Lamp 6.3 V

Electrical Element List